

# Côr™ Home Automation Garage Door Tilt Sensor TX-E401



## Product Data

### OVERVIEW

The TX-E Garage Door Tilt Sensor provides intrusion detection for garage structures. This sensor can be mounted on top of any garage door and allows for quick and easy installation without the need to align a magnet.

The TX-E Series Garage Door Tilt Sensor will transmit an open and close signal to the panel each time the garage door is opened or closed. When the alarm panel is armed, if the garage door opens to a forty-five degree angle, the sensor goes into an alarm condition that turns on the siren and initiates push notification, if notifications are turned on, or a call to the central monitoring station if professionally monitored. The TX-E Series Garage Door Tilt Sensor also features a slow loop response which eliminates false alarms triggered by garage door movement due to wind.

### STANDARD FEATURES

- Field proven wireless technology
- Case tamper
- Extended operating temperature range
- Slow loop response that eliminates false alarm due to wind
- Replaceable battery with up to 5 years of battery life (based on usage)
- 2 year warranty

### SPECIFICATIONS

Compatibility	Côr Home Automation Panel
Frequency	319MHz (Crystal based)
Battery	CR123A
Battery Life	5 years, typical
Operating Temperature	-22°F (-30°C) to 120°F (49°C)
Operating Humidity	5-95% non condensing
Weight	2.0 oz
Dimensions (W x H x D)	3.5 x 1.0 x 0.87 in. (8.89 x 2.54 x 2.20 cm)
Color	White
Approvals	FCC/IC



### ORDERING INFORMATION

TX-E401	Garage Door Tilt Sensor
---------	-------------------------